

Omnitechlink

Omnitechlink Network Keyboard



DATASHEET

KEY FEATURES

- ▶ Support Network connection, which is a truly convenient way for easy connection and control of Omnitelink NVR and PTZ camera
- ▶ Built-in Web Server can support the use of browser to easily manage and maintain the keyboard
- ▶ Support 4-axis variable speed joystick
- ▶ Designed with a LCD screen on operation panel, it is easy to display operations
- ▶ Support to control up to 110 devices
- ▶ Shortcut keys for PTZ control, such as preset, patrol and pattern
- ▶ Shortcut keys for NVR control, such as snapshot and audio operation
- ▶ Shortcut keys for recording and playback control, such as record, play, stop, pause, speed up and speed down
- ▶ Shortcut keys for light control operation
- ▶ Easy to operate, stable performance



Omnitechlink Network Keyboard



Model		OTL-K01
Control Mode		IP-based
Control Device		Omnitechlink NVR and PTZ camera
LCD Screen		58X44(2.8") Blue Screen
Joystick		4-axis joystick
Network		IPV4, HTTP, TCP, MSSP
External Interface	Network Interface	1*RJ45 100M/1000M
	Serial Interface	1*RS-232
General	Working Temperature	-10℃~55℃
	Working Humidity	20%~80%
	Power Supply	PoE (802.3af) / DC 12V 2A
	Power Consumption	5W MAX
	Weight	1.56Kg
	Dimensions	321mm(W)x179mm(D)x109mm(H)
	Warranty	2 Years

Omnitechlink Network Keyboard



Appearance

Operation Panel



1. Operation Shortcut Keys 2. Shuttle 3. LCD Screen 4. Joystick

Interfaces



1. RS-232 2. LAN 3. DC 12V 4. Power

Note: @2024 OmniTechLink is registered trademarks or trademark applications in various jurisdictions. All other company names and products are trademarks or registered trademarks of their respective companies. We reserve the right to introduce modifications without notice.



Contact Us: info@omnitechlink.com

www.omnitechlink.com



Headquarter: Via Real Collegio n. 2210024 Moncalieri (TO) Italy Tel: +3901119117660 Fax: +390110432483
MENA Branch: Business Center 1, M Floor, The Meydan Hotel, And Al Sheba, Dubai, U.A.E Tel: +971507127998

